



Main

| | |
|---------------------------|--|
| Range | MasterPact |
| Device short name | XF diag & com |
| Product or component type | Voltage release |
| Device application | Control |
| Range compatibility | Masterpact (MasterPact MTZ1) circuit-breaker |
| Voltage release type | Closing coil |

Complementary

| | |
|-------------------------------|---|
| Control type | Communicating |
| Signalling function | Electrical push-button activated Ready to close or open Error Coil powered |
| [Un] voltage power supply | 380...480 V AC 50/60 Hz |
| Threshold tripping voltage | 0.85...1.1 Un on closing |
| Holding power consumption | 4.5 VA |
| Circuit breaker mounting mode | Drawout |
| Maximum response time | 65 ms on closing for MasterPact MTZ1 |

Packing Units

| | |
|------------------------------|----------|
| Unit Type of Package 1 | PCE |
| Number of Units in Package 1 | 1 |
| Package 1 Height | 3.5 cm |
| Package 1 Width | 9.0 cm |
| Package 1 Length | 6.0 cm |
| Package 1 Weight | 1.167 kg |

Offer Sustainability

| | |
|----------------------------|---|
| REACH Regulation | REACH Declaration |
| EU RoHS Directive | Compliant EU RoHS Declaration |
| Mercury free | Yes |
| China RoHS Regulation | China RoHS Declaration |
| RoHS exemption information | Yes |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.