

Product data sheet

Characteristics

EY56SO332

Easy56 Socket - 3 Pin - 32A - 250V



Main

| | |
|---------------------------|------------------------|
| Product name | Easy56 |
| Product or component type | Socket-outlet |
| Device short name | EY56SO332 |
| Plug, socket category | Low voltage |
| Poles description | 1P + N + E |
| Network type | AC |
| Outlet standard | Australian/New Zealand |

Complementary

| | |
|-------------------------------------|----------------------------------------------------------------|
| Mounting mode | Surface mounted |
| Plug, socket, control station shape | Straight |
| [In] rated current | 32 A |
| Pin number | 3 pins |
| Shape of pin | Tubular |
| [Ue] rated operational voltage | 250 V |
| Network frequency | 50 Hz |
| Material | Polycarbonate: cover |
| Contacts material | Pins: brass |
| Connections - terminals | Screw terminals 4...16 mm ² rigid or stranded cable |
| Wire stripping length | 16 mm |
| Net weight | 0.471 kg |
| Height | 101 mm |
| Width | 101 mm |
| Depth | 101 mm |
| Colour | Grey (RAL 7035) |

Environment

| | |
|---------------------------------------|-----------------------------|
| Standards | AS/NZS 3123 |
| IP degree of protection | IP66 conforming to AS 60529 |
| Ambient air temperature for operation | -25...75 °C |
| Ambient air temperature for storage | -25...75 °C |

Offer Sustainability

| | |
|-------------------|---------------------|
| EU RoHS Directive | Under investigation |
|-------------------|---------------------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.