

## Product data sheet

### Characteristics

# PDL860M16WTWH

## 1-Way Half Standard Printed Switch Module; 16A/16AX, 1P, WASTE Legend, White



### Main

|                           |                   |
|---------------------------|-------------------|
| Range of product          | Modena 800 Series |
| Product or component type | Switch module     |
| Control type              | Rocker            |
| Colour tint               | White             |
| Quantity per set          | Set of 20         |
| Type of packing           | Carton            |

### Complementary

|                                |  |
|--------------------------------|--|
| Material                       | PC (polycarbonate)   |
| Surface finish                 | Matt   |
| Installation direction         | Vertical<br>Horizontal   |
| Width                          | 12.4 mm  |
| Height                         | 45.5 mm  |
| Depth                          | 21.45 mm   |
| Rated current                  | 16 A<br>16 AX  |
| [Ue] rated operational voltage | 250 V  |
| Network type                   | AC   |
| Network number of phases       | 1 phase  |
| Marking                        | Waste  |
| Mounting mode                  | Front  |
| Cable composition              | 9 x 1 mm <sup>2</sup><br>6 x 1.5 mm <sup>2</sup><br>3 x 2.5 mm <sup>2</sup><br>2 x 4 mm <sup>2</sup> |
| Connector type                 | #1 Square Head/#2 Phillips Screw   |

### Packing Units

|                              |          |
|------------------------------|----------|
| Unit Type of Package 1       | PCE      |
| Number of Units in Package 1 | 1        |
| Package 1 Height             | 1.2 cm   |
| Package 1 Width              | 4 cm     |
| Package 1 Length             | 4.5 cm   |
| Package 1 Weight             | 0.016 kg |

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

## Offer Sustainability

|                            |   |
|----------------------------|---|
| Sustainable offer status   | Green Premium product                         |
| EU RoHS Directive          | Compliant with Exemptions                     |
| Mercury free               | Yes   |
| China RoHS Regulation      | <a href="#">China RoHS Declaration</a>        |
| RoHS exemption information | <a href="#">Yes</a>                           |
| Environmental Disclosure   | <a href="#">Product Environmental Profile</a> |
| Circularity Profile        | No need of specific recycling operations      |