



Main

| | |
|---------------------------|--|
| Range | MasterPact |
| Device short name | MX diag & com |
| Product or component type | Voltage release |
| Device application | Control |
| Range compatibility | Masterpact MasterPact MTZ2 circuit-breaker Masterpact MasterPact MTZ3 circuit-breaker Masterpact MasterPact MTZ1 circuit-breaker |
| Voltage release type | Opening coil |

Complementary

| | |
|-------------------------------|--|
| Control type | Communicating |
| Signalling function | Error Electrical push-button activated Ready to close or open Coil powered |
| [Un] voltage power supply | 380...480 V AC 50/60 Hz |
| Threshold tripping voltage | 0.7...1.1 Un on opening |
| Holding power consumption | 4.5 VA |
| Circuit breaker mounting mode | Fixed |
| Maximum response time | 60 ms on opening for MasterPact MTZ1 60 ms on opening for MasterPact MTZ2 60 ms on opening for MasterPact MTZ3 |

Packing Units

| | |
|------------------------------|----------|
| Unit Type of Package 1 | PCE |
| Number of Units in Package 1 | 1 |
| Package 1 Height | 3.5 cm |
| Package 1 Width | 9.0 cm |
| Package 1 Length | 6.0 cm |
| Package 1 Weight | 1.162 kg |

Offer Sustainability

| | |
|----------------------------|---|
| Sustainable offer status | Green Premium product |
| REACH Regulation | REACH Declaration |
| EU RoHS Directive | Compliant with Exemptions |
| Mercury free | Yes |
| China RoHS Regulation | China RoHS Declaration |
| RoHS exemption information | Yes |
| Environmental Disclosure | Product Environmental Profile |
| Circularity Profile | End Of Life Information |