



## Main

|                           |  |
|---------------------------|--|
| Range                     | MasterPact                                   |
| Device short name         | XF diag & com                                |
| Product or component type | Voltage release                              |
| Device application        | Control                                      |
| Range compatibility       | Masterpact (MasterPact MTZ1) circuit-breaker |
| Voltage release type      | Closing coil                                 |

## Complementary

|                               |   |
|-------------------------------|---|
| Control type                  | Communicating   |
| Signalling function           | Error<br>Ready to close or open<br>Coil powered<br>Electrical push-button activated |
| [Un] voltage power supply     | 277 V AC 50/60 Hz   |
| Threshold tripping voltage    | 0.85...1.1 Un on closing  |
| Holding power consumption     | 4.5 VA  |
| Circuit breaker mounting mode | Drawout   |
| Maximum response time         | 65 ms on closing for MasterPact MTZ1  |

## Packing Units

|                              |          |
|------------------------------|----------|
| Unit Type of Package 1       | PCE      |
| Number of Units in Package 1 | 1        |
| Package 1 Height             | 9.0 cm   |
| Package 1 Width              | 6.0 cm   |
| Package 1 Length             | 8.0 cm   |
| Package 1 Weight             | 1.169 kg |

## Offer Sustainability

|                            |   |
|----------------------------|---|
| REACH Regulation           | <a href="#">REACH Declaration</a>             |
| EU RoHS Directive          | Compliant <a href="#">EU RoHS Declaration</a> |
| Mercury free               | Yes   |
| China RoHS Regulation      | <a href="#">China RoHS Declaration</a>        |
| RoHS exemption information | <a href="#">Yes</a>                           |