## **RM35TF30**

Harmony, 3 phase supply control relay, range 220 to 480 VAC, sequence, phase failure, phase imbalance, voltage





#### Main

Range of product	Harmony Control Relays
Relay type	Multifunction control relay
Product or component type	3-phase control relay
Product specific application	For 3-phase supply
Relay name	RM35TF
Relay monitored parameters	Undervoltage and overvoltage in window mode Phase sequence Phase failure detection Asymmetry
Time delay	Adjustable 0.110 s, +/- 10 % of the full scale value Tt- time delay upon fault
Switching capacity in VA	1250 VA
Measurement range	220480 V AC
Contacts type and composition	2 C/O
[Uc] control circuit voltage	220480 V

#### Complementary

Complementary	
Reset time	1500 ms at 480 V
Maximum switching voltage	250 V AC
	250 V DC
Minimum switching current	10 mA at 5 V DC
Maximum switching current	5 A AC
	5 A DC
[Un] rated nominal voltage	, self-powered
Supply voltage limits	194528 V AC, 3 phases
Control circuit voltage limits	- 12 % + 10 % Un
Power consumption in VA	022 VA at 400 V AC 50 Hz
Voltage detection threshold	< 194 V
Control circuit frequency	5060 Hz +/- 10 %
Output contacts	2 C/O
Nominal output current	5 A
Measurement voltage limits	176528 V AC
Hysteresis	2 %
Delay at power up	650 ms
Maximum measuring cycle	140 ms measurement cycle as true rms value
Threshold adjustment voltage	220 % of Un selected
	-122 % in the range 220 V AC
	+2+10 % in the range 480 V AC
Voltage range	220480 V phase to phase
Adjustment of asymmetry threshold	515 % of Un selected
Repeat accuracy	0.3 % for time delay
	0.5 % for input and measurement circuit
Measurement error	< 1 % over the whole range with voltage variation
	0.05 %/°C with temperature variation

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not inherent or and is not to be used for determining suitability or inhability of these products for specific user applications. It is the dourn aren in integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

Response time	< 200 ms (in the event of a fault)
Marking	CE
Overvoltage category	III conforming to IEC 60664-1
Insulation resistance	> 500 MOhm at 500 V DC conforming to IEC 60255-5 > 500 MOhm at 500 V DC conforming to IEC 60664-1
[Ui] rated insulation voltage	400 V conforming to IEC 60664-1
Supply frequency	50/60 Hz +/- 10 %
Operating position	Any position without derating
Connections - terminals	Screw terminals, 1 x 0.51 x 4 mm² (AWG 20AWG 11) solid without cable end Screw terminals, 2 x 0.52 x 2.5 mm² (AWG 20AWG 14) solid without cable end Screw terminals, 1 x 0.21 x 2.5 mm² (AWG 24AWG 12) flexible with cable end Screw terminals, 2 x 0.22 x 1.5 mm² (AWG 24AWG 16) flexible with cable end
Tightening torque	0.61 N.m conforming to IEC 60947-1
Housing material	Self-extinguishing plastic
Local signalling	LED (green) for power ON LED (yellow) for relay ON LED (yellow) for fault
Mounting support	35 mm symmetrical DIN rail conforming to IEC 60715
Electrical durability	100000 cycles
Mechanical durability	30000000 cycles
Operating rate	<= 360 operations/hour full load
Utilisation category	AC-12 conforming to IEC 60947-5-1 AC-13 conforming to IEC 60947-5-1 AC-14 conforming to IEC 60947-5-1 AC-15 conforming to IEC 60947-5-1 DC-12 conforming to IEC 60947-5-1 DC-13 conforming to IEC 60947-5-1
Safety reliability data	MTTFd = 399.5 years B10d = 360000
Width	35 mm
Net weight	0.13 kg
Control type	Without test button

#### Environment

Electromagnetic compatibility	Emission standard for industrial environments conforming to IEC 61000-6-4  Emission standard for residential, commercial and light-industrial environments
	conforming to IEC 61000-6-3  Immunity for industrial environments conforming to IEC 61000-6-2
Standards	IEC 60255-1
Product certifications	GL[RETURN]UL[RETURN]CSA[RETURN]GOST[RETURN]C-Tick
Directives	89/336/EEC - electromagnetic compatibility 73/23/EEC - low voltage directive
Ambient air temperature for storage	-4070 °C
Ambient air temperature for operation	-2050 °C
Relative humidity	95 % at 55 °C conforming to IEC 60068-2-30
Vibration resistance	0.35 mm (f= 557.6 Hz) conforming to IEC 60068-2-6 1 gn (f= 57.6150 Hz) conforming to IEC 60255-21-1
Shock resistance	15 gn for 11 ms conforming to IEC 60255-21-1
IP degree of protection	IP20 (terminals) conforming to IEC 60529 IP30 (casing) conforming to IEC 60529
Pollution degree	3 conforming to IEC 60664-1
Dielectric test voltage	2 kV, 1 min AC 50 Hz
Non-dissipating shock wave	4 kV

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.800 cm
Package 1 Width	7.800 cm
Package 1 Length	9.700 cm
Package 1 Weight	133.000 g
Unit Type of Package 2	S03
Number of Units in Package 2	48
Package 2 Height	30.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	7.070 kg
Unit Type of Package 3	P06
Number of Units in Package 3	384
Package 3 Height	75.000 cm
Package 3 Width	60.000 cm
Package 3 Length	80.000 cm
Package 3 Weight	64.124 kg

## Offer Sustainability

Sustainable offer status	Green Premium product
REACh Regulation	☑REACh Declaration
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)
Mercury free	Yes
China RoHS Regulation	☑ China RoHS Declaration
RoHS exemption information	₫Yes
Environmental Disclosure	Product Environmental Profile
Circularity Profile	End Of Life Information


#### Contractual warranty


Warranty	18 months

# **RM35TF30**

### Multifunction 3-Phase Supply Control Relays

#### **Dimensions and Mounting**






# Product data sheet Connections and Schema

# **RM35TF30**

#### Multifunction 3-Phase Supply Control Relays


## Wiring Diagram




# **RM35TF30**

#### **Function Diagrams**

Phase Sequence Control, Phase Failure Detection (U measured < 0.7 x nominal supply voltage) and Asymmetry Detection



#### Control of Overvoltage and Undervoltage in Window Mode



#### Legend

A Asymmetry thershold

Tt Time delay after crossing of threshold

H Hysteresis

U> Overvoltage threshold

U< Undervoltage threshold

L1, L2, L3 Phases of the supply voltage monitored

R Output relay

Relay status: black color = energized.